

StandAlone Proximity

SecuraKey Proximity Readers



The American Access Systems line of **StandAlone Proximity** card readers combine the latest in proximity technology with the ease of non PC programming.

Each **StandAlone Proximity** unit features a high grade stainless steel faceplate with heavy metal, powder coated enclosure. Mounted to the face plate is a SecuraKey Proximity reader with the controller board safely mounted inside the enclosure. Simply unlock the faceplate and program the unit from the enclosed keypad. That's it. It's that simple!

All **StandAlone Proximity** card readers have a real time transaction that can be printed out on an RS-232 serial port printer #21-047. The unit will report time, date, card number entered, relay activated and valid / invalid card.

When more than one card reader is needed at an access point, choose model #23-213(i). This unit allows an additional "slave" proximity reader (see the AAS **RemotePro CR** line) to be wired to it, making it the ideal product for an entry / exit application or where two proximity readers are needed.



AMERICAN
ACCESS SYSTEMS

SecuraKey Proximity Card Readers

General Specifications



23-213

Stand Alone Unit

- Input: 16.5VAC (transformer included)
- Output: n/o or n/c contact 1-99 seconds
- Operating temperature: -15 to 175 Fahrenheit
- Dimensions: 6.625" H x 5.50" W x 4.25"D
- Intercom: 8 ohm Mylar speaker w/ call button
- Ship weight: 5 lbs.
w/ intercom: 7lbs.

Relay Specs

	<u>DC Load</u>	<u>AC Load</u>
Contact Rating	1A @ 24V	.5A @ 120V
Max. switching voltage	150V	220V
Max. carrying current	2A	2A
Max. switching power	28W	60VA

Features

- 2000 card capability
- Programmable Personal Master Code
- Programmable Latch / Unlatch Card
- Programmable Sleep Card
- Three strikes – you're out
- True Anti Pass Back
- 1000 code transaction buffer
- Optional camera
- LED indicators
- Non - volatile memory
- Night Light
- Limited two year warranty



23-213i

with Intercom

23-213 and 23-213i only

- Two relays
- Split-relay function:
 - allows user to activate two separate doors / gates
- Compatible with one "slave" unit
 - refer to the AAS RemotePro CR line



AMERICAN
ACCESS SYSTEMS

